



PRODUCT SPECIFICATIONS
For more information visit www.hagerco.com

2-659-0185 - Wireless Transmitter, Hardwires to Actuator

2-659-0185

9-Volt Wireless Transmitter Hardwired to Actuator



Applications

Used for wireless activation of any type of automatic doors
with a wireless receiver (433MHz)
Converts hardwired push actuators to wireless

CE IC

PRODUCT SPECIFICATIONS

Accessories:

2-659-0183 - Wireless Receiver (433MHz)

Box Quantity:

1

Case Quantity:

20

Certifications:

CE, FCC, IC

Electrical Specifications:

Radio Control Type: Digital
Emitted Radio Power: -28.7dBm
(transmitter)

Features:

Transmitters can be programmed to multiple receivers
Wire leads plug into terminals on Hager actuators to convert
hardwired actuators to wireless

Frequency:

433 MHz

LED Indicators:

Red = Transmitter Active

Notes:

Not recommended for wave to open actuators

Size:

2.75" (Height)
1.375" (Width)
1" (Depth)

Voltage:

9V Battery

Warranty:

1 Year